

## YL561A101

MOTORISED CHANGEOVER SWITCH 1-0-2 2P 160A INCOMING ON TOP. 12V DC



 Code
 007YL561A101

**EAN** 8430892216555

## **Product description**

Motorised changeover switch 1-0-2, 2 poles 160A with motor unit supply 12Vdc . The supply incoming cables are connected on the top side of the unit and the load outgoing cables are connected on the bottom side. Size D3 dimensions 185x195x113, includes auxiliary contact 12A. Back plate mounting. Built-in internal links, mechanical and electrical interlock. Local emergency operation, includes removable padlockable handle. Display for switch position indication and operation counter.Impulse control logic. Protection against supply voltage failure . Terminal connection with tubular cable lugs M8 up to 120mm2.

## Logistic data

Logiotio data	
Customs code	85365080
ETIM code	EC000216
Technical data	
Poles	2
Rated voltage / frequency	690 V / 50 Hz
Operational rating (le)	160 A
Thermal rating (lth)	160 A
Wire cross section	70 mm <sup>2</sup>
Tightening torque	6 Nm
Connection screws	M8
Terminal	
Peak consumption	2,5 A
Nominal consumption	40 mA
Weight	2850 gr
Supply voltage (V DC)	12 V +15%
Standard	IEC 60947-3
Y5 Type	56
Supply	12V DC

## Connection

