

YL5627101

MOTORISED CHANGEOVER SWITCH 1-0-2 3P 100A INCOMING ON TOP. 12V DC



| | |
|-------------|---------------|
| Code | 007YL5627101 |
| EAN | 8430892213660 |

Product description

Motorised changeover switch 1-0-2 , 3 poles 100A with motor unit supply 12Vdc . The supply incoming cables are connected on the top side of the unit and the load outgoing cables are connected on the bottom side. Size D2 dimensions 147x178x113, includes auxiliary contact 12A. Back plate mounting. Built-in internal links, mechanical and electrical interlock. Local emergency operation, includes removable padlockable handle. Display for switch position indication and operation counter. Impulse control logic. Protection against supply voltage failure . Cable clamp connection for wires 16-50mm².

Logistic data

| | |
|--------------|----------|
| Customs code | 85365080 |
| ETIM code | EC000216 |

Technical data


| | |
|---------------------------|-----------------------|
| Poles | 3 |
| Rated voltage / frequency | 690 V / 50 Hz |
| Operational rating (Ie) | 100 A |
| Thermal rating (Ith) | 100 A |
| Wire cross section | 16-50 mm ² |
| Tightening torque | 3,5 Nm |
| Connection screws | M8 |

Terminal



| | |
|-----------------------|-------------|
| Peak consumption | 2,5 A |
| Nominal consumption | 40 mA |
| Weight | 2250 gr |
| Supply voltage (V DC) | 12 V +15% |
| Standard | IEC 60947-3 |
| Y5 Type | 56 |
| Supply | 12V DC |

Connection



Dimensions

